

∞ **Ranges from 40dB to 130dB at frequencies between 31.5Hz and 8**
KHz.

∞ **Display with 0.1dB steps on a 4-digits LCD.**

∞ **With one equivalent weighted sound pressure level A**

∞ **Auto Power Off**

∞ **Auto Backlit**

Frequency range 31.5Hz~8KHz

Measuring level range 40~130dB

Frequency weighting A

Microphone 1/2 inch Electric condenser microphone

Display Up data 0.5 sec.

Time weighting FAST (125mS)

Accuracy + 3.5dB @1kHz, 94dB (under reference conditions)

Alarm function "OVER" is show when input is out of range (>130dB)

Auto power off Meter automatically shuts down after approx. 15 minutes of inactivity.

Power supply One 9V battery, 006P or IEC 6F22 or NEDA 1604.